



**Description:** SKINDICHT RWV\_  
**Lapp code:** Lapp 52004190

The **Test voltage** of the cable Lapp 52004190 is /.

## Application range

- Angled glands are used in areas where cables have to run in parallel to the housing wall.
- Electric motor manufacturing
- Machine and equipment manufacturing
- Plant engineering
- Light and sound applications

## Product Make-up

- PG connection thread

In our Cable list on next page you can find all interesting information acc. article Lapp 52004190 and much more.

CABLE LIST - all informations you need you can find here

Product Name	Lapp Nr.	Article designation / size	A [mm]	G mm	Ø-B mm	Incised sealing ring ØF (mm)	Overall length/ C (mm)	Thread length/ D (mm)	SW1/SW2 mm	Pieces / PU
SKINDICHT® RWV										
SKINDICHT RWV	Lapp 52004180	RWV 7	20.5	14	15.3	5	26.0	8.5	15 / 13	25
SKINDICHT RWV	Lapp 52004190	RWV 9	23.5	17	18.3	5/8	28.0	9.5	18 / 15	25
SKINDICHT RWV	Lapp 52004200	RWV 11	26.0	20	21.9	7/10/12.5	31,5	10.0	21 / 18	25
SKINDICHT RWV	Lapp 52004210	RWV 13,5	28.5	22	24.0	7/10.5/13/16	34,5	10.5	23 / 20	25
SKINDICHT RWV	Lapp 52004220	RWV 16	31.0	24	26.1	8/10.5/13.5/16	35,5	11.0	26 / 22	10
SKINDICHT RWV	Lapp 52005420	RWV 21	33.5	30	32.5	11/15/18/20	42,5	11.5	32 / 28	10
SKINDICHT RWV	Lapp 52004225	RWV 29	43.0	40	42.0	19/23/27/31	49.0	13.0	41 / 37	10
SKINDICHT® RWV without E+D										
SKINDICHT RWV	Lapp 52024020	RWV 7	20.5	14	15.3		20,2	8.5	15 / 13	25
SKINDICHT RWV	Lapp 52023970	RWV 9	23.5	17	18.3		21,8	9.5	18 / 15	25
SKINDICHT RWV	Lapp 52023980	RWV 11	26.0	20	21.9		24,9	10.0	21 / 18	25
SKINDICHT RWV	Lapp 52023990	RWV 13,5	28.5	22	24.0		27,4	10.5	23 / 20	25
SKINDICHT RWV	Lapp 52024000	RWV 16	31.0	24	26.1		28,5	11.0	26 / 22	10
SKINDICHT RWV	Lapp 52024010	RWV 21	33.5	30	32.5		34,8	11.5	32 / 28	10
SKINDICHT RWV	Lapp 52024015	RWV 29	43.0	40	42.0		41,2	13.0	41 / 37	10